

Generator Interconnection Facility Study Report

for the

for

Jerome, Gooding and Lincoln Counties, Idaho

February 09, 2023

FACILITY STUDY REPORT (FSR)

Project #635 February 09, 2023

1. <u>General Facility Description</u>

a 1000 MWac and connection Customer") has stated that the proposed project will consist of and connect to the 500 kV bus at Idaho power Company (IPC) in Jerome County, Idaho. The total project output as studied is 1000 MW.

Contact Information for Interconnection Customer is as follows:



A Standard Large Generator Interconnection Agreement (the "LGIA") under IPC's Open Access Transmission Tariff (OATT) between Interconnection Customer and IPC – Delivery (Transmission Provider) for the second seco

Project Queue and Affected Systems:

The Project has applied to connect to the Idaho Power's transmission system for an injection of 1000 MW at two Points of Interconnection (POI) at 500kV to IPC's/PacifiCorp's (PAC's) jointly owned station. Because the proposed interconnection is to the jointly owned station, PacifiCorp is an Affected Party.

If an earlier queue project that is responsible for providing additional transmission capacity should drop out of the queue, a later queue project that may have been relying on at least a portion of any "surplus" capacity may then be faced with additional project costs for transmission capacity additions of their own. As of the date of this report, there are projects in the queue (GI #530, GI #549, GI #551, GI #557, GI# 558, GI #567, GI #570/#587, GI #588, GI #590, GI # 604, GI #605, GI# 613, GI #614/#616, GI# 619, GI #620, GI #621, GI #622, GI #624, GI #625, GI #629, GI #630, GI #632, GI #633, and GI #634) ahead of for the project should be passed on to the Project should changes be made to their queue position or generation output.

The recommended upgrades for GI #530, GI #549, GI #551, GI #557, GI# 558, GI #567, GI #570/#587, GI #588, GI #590, GI # 604, GI #605, GI# 613, GI #614/#616, GI# 619, GI #620, GI #621, GI #622, GI #624, GI #625, GI #629, GI #630, GI #632, GI #633, and GI #634 were assumed to be completed prior to the interconnection of the Project.

There are identified contingent facility Network Upgrades for GI #635 that are required to be completed prior to the interconnection of this Project. As of the date of this report, there is no estimated completion date associated with these contingent facilities. The upgrades may take longer to construct than the Interconnection Facilities and Network Upgrades for this Project. Details on the contingent facilities identified are in Appendix B. For this and other reasons, the cost estimates included in this FSR are estimates only, are based on currently known or assumed facts that may not be accurate or materialize and are subject to change

1.1 Interconnection Point

The Interconnection Facilities are located in IPC's Southern region in Township , Range and Section . The Points of Interconnections ("POI") for the Project will be in the new 500 kV station at the node connecting switches 534C and 535B as well as at the node connecting switches 537C and 538B. A drawing identifying the POI's is attached as Exhibit 1 (Midpoint South 500kV Station).

1.2 Point of Change of Ownership

The Points of Change of Ownership for the Project will be on the Interconnection Customer's side of disconnect switches & . A drawing identifying the Points of Change of Ownership is attached as Exhibit 1 (Station).

1.3 Interconnection Customer's Facilities

The Interconnection Customer's Facilities are located approximately mile away from IPC's Interconnection Facilities. The Interconnection Customer will install wind turbines 4.60/4.20 MVA/MW generators, batteries, inverters, disconnect switches, distribution collector system, transformers (including four main step-up transformers), controllers, appropriate grounding measures, and associated auxiliary equipment. The main step-up transformers are 500/34.5 kV GSU transformers 240/320/400 MVA Wye-Ground/Wye-Ground and a delta included in the transformer to create a solid ground path for the transmission system. Interconnection Customer will build facilities to the Points of Change of Ownership.

The Interconnection Customer's system will be constructed as follows:

- 1. 500kV transmission line (Project to POI)
- transformers 240/320/400 MVA Wye-Ground/Wye-Ground
 4.60/4.20 MVA/MW with a Power Factor 0.895
- with connected at each of the transformer
 4. with connected at each of the transformer
- 5. A plant controller will be used to control the inverter system and to implement smart inverter functionality for operating the project within a voltage range and power factor specified by IPC at the Point of Interconnection

The above referenced inverters, or equivalent inverters that have the same specifications and functionality as stated above must be utilized. If a different inverter is utilized that has different specifications and functionality than that which was studied then additional study and/or equipment may be necessary.

1.4 Other Facilities Provided by Interconnection Customer

1.4.1 Telecommunications

The Interconnection Customer is not responsible for any third party communication circuits for the IPC Interconnection Facilities. Any additional telecommunication requirements will be the sole responsibility of the Interconnection Customer.

1.4.2 Ground Fault Equipment

The Interconnection Customer will install transformer configurations that will provide a ground source to the transmission system.

1.4.3 Generator Output Limit Control

The Interconnection Customer will install equipment to receive signals from IPC Grid Operations for Generation Output Limit Control ("GOLC") - see Section 3 Operating Requirements and Appendix A. IPC's recommended method of communication for GOLC is via fiber between the Interconnection Station and the Project.

1.4.4 Local Service

The Interconnection Customer is responsible to arrange for local service to their site, as necessary.

1.4.5 Property

This project will require expansion of the 500 kV yard at Substation. This expansion will require land to be purchased to the south of the existing facility. The work described in sections 5.2 and 5.3 are contingent upon the successful acquisition of this land. Actual cost and anticipated time line to acquire the land is not included in this report. Approximately of land would need to be purchased and payment would be the responsibility of the Interconnect Customer.

1.4.6 Monitoring Information

If the Interconnection Customer requires the ability to monitor information related to the IPC breaker/relay (i.e., Mirrored Bits) in the interconnection station, they are required to supply their own communications circuit. The fiber communication circuit used for GOLC is acceptable.

1.4.7 Generator Technical Information & Drawings

Interconnection Customer shall provide draft design prints during FSR development containing technical information, like impedances, and equipment brand and models. After construction, the Interconnection Customer shall submit to IPC all the as-built information, including prints with the latest approved technical information and commissioning test results.

1.4.8 Meteorological Data

In order to integrate the wind energy into the IPC system, the Interconnection Customer will provide weather data to IPC from the proposed Project site or from a location within two miles of the Project site consisting of the following near real-time weather parameters that will be collected via each meteorological observation tower at 10 m & 80 m above ground: Wind Speed (miles/seconds), Wind Direction, Air Temperature (degrees Centigrade), along with Relative Humidity, and Barometric Pressure. This data shall be provided to IPC hourly via commonly accepted electronic web service standards or similar communication method. Specific meteorological data must also be sent over the DDS communication circuit as identified in Appendix A.

Interconnection Customer will provide relevant historical meteorological data to IPC. Additionally, the Interconnection Customer shall submit to IPC the physical and technical specifications for all meteorological measurement devices, geographic locations and technical specifications of all turbines. The associated cost for obtaining this data is the Interconnection Customer responsibility and therefore not included in the Facility Study estimate.

1.4.9 Generator Technical Information & Drawings

Interconnection Customer shall provide draft design prints during FSR development containing technical information, like impedances, and equipment brand and models. After construction, the Interconnection Customer shall submit to IPC all the as-built information, including prints with the latest approved technical information and commissioning test results.

1.5 IPC's Interconnection Facilities

Transmission Provider's Interconnection Facilities are referred to hereafter as "IPC's Interconnection Facilities." IPC will install at the new **Station** Station, two ION 8650A meters, two dead-end structures, two 500 kV air break switches, six CTs, required foundations, bus, bus supports and fiber communication equipment to allow the Interconnection Customer to interconnect the project. IPC will install facilities up to the Point of Change of Ownership.

IPC will install equipment to collect and transmit Phasor Measurement Unit (PMU) data to IPC. The data can be made available to the Interconnection Customer on request.

The minimum acceptable PMU message rate is 30 messages per second. The minimum set of PMU measurement channels recorded at the POI is shown below. Additional or substitute channels may be required on a per case basis depending on the interconnection configuration and facility design details.

- Frequency
- Frequency Delta (dF/dt)
- Positive Sequence Voltage Magnitude
- Positive Sequence Voltage Angle
- Positive Sequence Current Magnitude
- Positive Sequence Current Angle

2. Estimated Milestones

These milestones will begin, and the construction schedule referenced below will only be valid, upon receipt of funding from Interconnection Customer or its authorized third party no later than the date set forth below for such payment. IPC will not commit any resources toward project construction that have not been funded by Interconnection Customer. Additionally, failure by Interconnection Customer to make the required payments as set forth in this Study by the date(s) specified below may result in the loss of milestone dates and construction schedules set forth below. In the event that the Interconnection Customer is unable to meet dates as outlined below, Interconnection Customer may request an extension of the Operation Date of up to three (3) years. Interconnection Customer's request will be evaluated by IPC to ensure Interconnection Customer's request does not negatively impact other projects in IPC's Generator Interconnection Queue. Such extension will be allowed only if IPC determines, in its sole

discretion, that the extension will not negatively impact other projects in IPC's Generator Interconnection Queue. Estimated milestones, which will be updated and revised for inclusion in the LGIA in light of subsequent developments and conditions, are as follows:

Estimated Date	Responsible Party	Estimated Milestones
[DATE]	Interconnection Customer	IPC receives Notice to Proceed for design, procurement and construction.
		Construction funding or arrangements acceptable to IPC are made with IPC's Credit Department
24 months after construction funds received	IPC	IPC Engineering and Design Complete
30 months after construction funds received	IPC	IPC Long Lead Material Procured/Received
6 months prior to IPC Commissioning	IPC	New generation must be modeled and submitted to the Western Energy Imbalance Market a minimum of 6 months prior to coming online, failure to submit by given lead time will results in project delay.
48 months after construction funds received	IPC	IPC Construction Complete
49 months after construction funds received	IPC	IPC Commissioning Complete
Approx. 2026	IPC	Contingent facilities completed. (Appendix B items 1-5)
Approx. 2028	IPC	Contingent facilities completed. (Appendix B item 6)
5 days after switching request made to IPC Dispatch	Interconnection Customer	Switch at the Point of Interconnection can be closed
TBD	IPC	Notification from IPC's Energy Contracting Coordinator confirming First Energy of Non- Firm Output
TBD	Interconnection Customer	Interconnection Customer testing begins
TBD	IPC	Notification from IPC's Energy Contracting Coordinator confirming Operation Date (pending all requirements are met) of Firm Network Resource Output

IPC does not warrant or guarantee the foregoing estimated milestone dates, which are estimates only. These milestone dates assume, among other things, that materials can be timely procured, labor resources are available, and that outages to the existing transmission system are available to be scheduled.

Additionally, there are several matters, such as permitting issues and the performance of subcontractors that are outside the control of IPC that could delay the estimated Operation Date. For purposes of example only, federal, state, or local permitting, land division approval, identification of Interconnection Facilities location, access to proposed Interconnection Facilities location for survey and geotechnical investigation, coordination of design and construction with the Interconnection Customer, failure of IPC's vendors to timely perform services or deliver goods, and delays in payment from Interconnection Customer, may result in delays of any estimated milestone and the Operation Date of the project. To the extent any of the foregoing are outside of the reasonable control of IPC, they shall be deemed Force Majeure events.

3. **Operating Requirements**

The Project is required to comply with the applicable Voltage and Current Distortion Limits found in IEEE Standard 519-2014 *IEEE Recommended Practices and requirements for harmonic Control in Electrical Power Systems* or any subsequent standards as they may be updated from time to time.

The Project will be subject to reductions directed by IPC Grid Operations during transmission system contingencies and other reliability events. When these conditions occur, the Project will be subject to Generator Output Limit Control ("GOLC") and will have equipment capable of receiving an analog setpoint via DNP 3.0 from IPC for GOLC. Generator Output Limit Control will be accomplished with a setpoint and discrete output control from IPC to the Project indicating maximum output allowed. For more detail see Appendix A.

Low Voltage Ride Through: The Project must be capable of riding through faults on adjacent sections of the power system without tripping due to low voltage. The interconnection projects must meet or exceed the Low Voltage Ride-Through requirements as set forth in NERC Standard PRC-024.

Frequency Response Requirements: Generator must be capable of providing Fast Frequency Response for both positive and negative frequency deviations from 60Hz (+/- 0.036 Hz) for Bulk Electric System disturbances. The required frequency response will be linear for a deviation of 0 to +/- 0.1 Hz, a response of 0% to 3% of generator capacity, with a maximum required response of 3% of generator's full capacity for as long as the generator is able to provide support or the frequency deviation is reduced to within stated limits, whichever occurs first. Provided that Generator meets the above Fast Frequency Response requirements, Company shall not curtail Interconnection Customer when such curtailments are caused by a need to comply with applicable Frequency Responsive reliability standards.

Momentary Cessation Requirements: Momentary cessation should not be used within the voltage and frequency ride-through curves specified in PRC-024. Use of momentary cessation is not considered "ride through" within the "No Trip" zone curves of PRC-024. The use of momentary cessation should be eliminated to the extent possible consistent with NERC's *Reliability Guideline for BPS-Connected Inverter-Based Resource Performance*.

Interconnection Customer will be able to modify power plant facilities on the Interconnection Customer side of the Pint of Change of Ownership with no impact upon the operation of the transmission or distribution system whenever the generation facilities are electrically isolated from the system via the disconnect switches **and and a terminal clearance is issued by IPC's** Grid Operator.

4. Reactive Power

It is the Project's responsibility to provide reactive power capability to have a power factor operating range of at least 0.95 leading (absorbing) to at least 0.95 lagging (supplying) at the high side of the generator substation over the range of real power output (up to maximum output of the project).

The Project must have equipment capable of receiving an analog setpoint, via DNP 3.0, from IPC for Voltage Control. IPC will issue an operating voltage schedule for the Project at the time the LGIA is executed. For more detail see Appendix A.

5. Upgrades

5.1 Upgrades to Distribution System

No distribution network upgrades are required.

5.2 Network Upgrades to Substations

IPC will expand the existing **product of the station** station to add two 500kV lines bays to feed a new station to the south. The expansion will include two 500kV line bays, with two steel dead-end structures, three 500kV circuit breakers, six 500kV air-break switches, six CCVTs, and associated bus supports, foundations, relaying, communications, and control equipment will be installed in the station yard and building.

IPC will also install a new **Sector and Sector and Sect**

5.3 Network Upgrades to Transmission System

IPC will install two 500kV transmission lines from switchyard. Line length is approximately 0.25 mile for

switchyard. Line length is approximately 0.25 mile for and 0.25 mi

(1) 96 count OPGW -

. New transmission structures are in

vertical configuration. Phases will roll horizontal into the sub bays.

6. Estimated Costs

The following good faith estimates are provided in 2023 dollars and are based on a number of assumptions and conditions. IPC does not warrant or guarantee the estimated costs in the table below, which are estimates only and are subject to change. Interconnection Customer will be responsible for all actual costs incurred in connection with the work to be performed by IPC and its agents, under the terms and subject to the conditions included in any LGIA executed by IPC and Interconnection Customer. Overhead costs cover the indirect costs associated with the Project and may vary from time to time.

The estimated cost below is required to be paid in full by the Interconnection Customer, or other arrangements acceptable to IPC are made with IPC's Credit Department, prior to IPC commencing construction on the project.

Estimated Cost:

Description	Ownership	Cost Estimate
IPC Interconnection Facilities:		
Facilities between the Point of Change of Ownership and Point of		
Interconnection as described in Section 1.5	IPC	\$2,251,765
Contingency 10%		\$225,177
Overheads 4.5%		\$111,462
TOTAL		\$2,588,404
Network Upgrades to IPC Substation		
Upgrades at existing yard & the new		
yard as described in Section 5.2	IPC	\$24,725,737
Contingency 10%		\$2,472,574
Overheads 4.5%		\$1,223,924
TOTAL		\$28,422,235
Network Upgrades to IPC Transmission		
Upgraded at as described in Section 5.3	IPC	\$ 3,066,558
Contingency 10%		\$306,656
Overheads 4.5%		\$151,795
TOTAL		\$3,525,008
GRAND TOTAL	\$34,535,647	

Note Price does not include cost of land

Note Regarding Transmission Service:

This FSR is a study of a request for Network Resource Interconnection Service. This FSR identifies the facilities necessary to provide such service. Network Resource Interconnection Service in and of itself does not convey any right to transmission service or to deliver electricity to any specific customer or Point of Delivery.

Note Regarding LGIA:

This FSR is a study and preliminary evaluation only and does not constitute, or form the basis of, a definitive agreement related to the matters described in this FSR. Unless and until a LGIA is executed by IPC and Interconnection Customer, no party will have any legal rights or obligations, express or implied, related to the subject matter of this FSR.

Appendix A

Generation Interconnection Control Requirements

A.1 Generator Output Limit Control (GOLC)

A.1.1 IPC requires Interconnected Power Producers to accept GOLC signals from IPC's energy management system ("EMS").

A.1.2 The GOLC signals will consist of four points shared between the IPC EMS (via the IPC RTU) and the Interconnection Customer's Generator Controller ("SGC"). The IPC RTU will be the master and the SGC will be the slave.

A.1.2.1 GOLC Setpoint: An analog output that contains the MW value the Interconnection Customer should curtail to, should a GOLC request be made via the GOLC On/Off discrete output Control point.
 A.1.2.1.1 An Analog Input feedback point must be updated (to reflect the GOLC setpoint value) by the SGC upon the SGC's receipt of the GOLC setpoint change, with no intentional delay.

A.1.2.2 GOLC On/Off: A discrete output (DO) control point with pulsing Trip/Close controls. Following a "GOLC On" control (DNP Control Code "Close/Pulse On"), the SGC will run power output back to the MW value specified in the GOLC Setpoint. Following a "GOLC Off" control (DNP Control Code "Trip/Pulse On"), the Interconnection Customer is free to run to maximum possible output.

A.1.2.2.1 A Discrete Input (DI) feedback point must be updated (to reflect the last GOLC DO Control Code received) by the SGC upon the SGC's receipt of the GOLC DO control, with no intentional delay. The feedback DI should latch to an OFF state following the receipt of a "GOLC OFF" control and it should latch to an ON state following the receipt of an "GOLC ON" control.

A.1.3 If a GOLC control is issued, it is expected to see MW reductions start within 1 minute and plant output to be below the GOLC Setpoint value within 10 minutes.

A.2 Voltage Control

A.2.1 IPC requires Transmission-Interconnected Power Producers to accept voltage control signals from IPC's EMS when they are connected to IPC's transmission system.

A.2.2 The voltage control will consist of one setpoint and one feedback point shared between the IPC EMS and the SGC.

A.2.3 The setpoint will contain the desired target voltage for plant operation. This setpoint will have a valid control range between 0.95 and 1.05 per unit ("p.u.") of nominal system voltage.

A.2.4 The control will always be active, there is no digital supervisory point like the Curtail On/Off control above.

A.2.4.1 When a setpoint change is issued an Analog Input feedback point must be updated (to reflect the voltage control setpoint value) by the SGC upon the SGC's receipt of the voltage control setpoint change, with no intentional delay.

A.2.4.2 When a setpoint change is received by the SGC, the voltage control system should react with no intentional delay.

A.2.4.3 The voltage control system should operate at the voltage indicated by the setpoint with an accuracy of $\pm 0.5\%$ of the nominal system voltage.

A.2.5 The Interconnection Customer should supervise this control by setting up "reasonability limits", i.e., configure a reasonable range of values for this control to be valid. As an example, they will accept anything in the valid control range (between 0.95 and 1.05 p.u.) but reject values outside this range. If they were fed an erroneous value outside the valid range, their control system would default to the last known, good value.

Digital Inputs to IPC (DNP Obj. 01, Var. 2)								
Index	Description	State (0/1)	Comments:					
			Feedback provided by					
0	GOLC Off/On (Control Feedback)	Off/On	Interconnection Customer					
	FREQUENCY RESPONSE OFF/ON		Feedback provided by					
1	(Control Feedback)	Off/On	Interconnection Customer					
	52A Interconnection Customer Main Breaker							
2	(if present)	Open/Closed	Sourced at substation					
	52A Interconnection Customer Capacitor							
3	Breaker (if present)	Open/Closed	Sourced at substation					

A.3 Generation Interconnection Data Points Requirements

Digital Outputs to Interconnection Customer (DNP Obj. 12, Var. 1)						
Index	Description	Comments:				
0	GOLC Off/On	Control issued by IPC				
1	Frequency Response Off/On	Control issued by IPC				

Analog Inputs to IPC (DNP Obj. 30, Var. 2)								
		Raw	Raw	EU	EU	EU		
Index	Description	High	Low	High	Low	Units	Comments:	
							Provided by	
	GOLC Setpoint Value Received		-				Interconnection	
0	(Feedback)	32767	32768	TBD	TBD	MW	Customer	
							Provided by	
	Voltage Control Setpoint Value Rec'd		-				Interconnection	
1	(Feedback)	32767	32768	TBD	TBD	kV	Customer	
							Provided by	
			-				Interconnection	
2	Maximum Park Generating Capacity	32767	32768	TBD	TBD	MW	Customer	
							Provided by	
			-			DEG	Interconnection	
3	Ambient Temperature	32767	32768	327.67	-327.68	С	Customer	
						Deg	Provided by	
			-			from	Interconnection	
4	Wind Direction	32767	32768	327.67	-327.68	North	Customer	
							Provided by	
			-				Interconnection	
5	Wind Speed	32767	32768	327.67	-327.68	M/S	Customer	
							Provided by	
			-				Interconnection	
6	Relative Humidity	32767	32768	TBD	TBD	%	Customer	

7	SPARE						
8	SPARE						
							Provided by
			-				Interconnection
9	Number of Turbines In High Speed Cutout	32767	32768	32767	-32768	Units	Customer
10	SPARE						
11	SPARE						
12	SPARE						
13	SPARE						
14	SPARE						
15	SPARE						
16	SPARE						
17	SPARE						

Analog Outputs to Interconnection Customer (DNP Obj. 41, Var. 2)									
		Raw		EU	EU	EU			
Index	Description	High	Raw Low	High	Low	Units	Comments:		
0	GOLC Setpoint	32767	-32768	TBD	TBD	MW	Control issued by IPC		
1	Voltage Control Setpoint	32767	-32768	TBD	TBD	kV	Control issued by IPC		
2	SPARE								
3	SPARE								
4	SPARE								
5	SPARE								
6	SPARE								
7	SPARE								
8	SPARE								
9	SPARE								

Appendix B

The following table B1 is a summary of the GI #635 contingent facility upgrades required as detailed in the GI #635 System Impact Report dated October 14, 2022.



Table B1: GI #635 Transmission Upgrades Required