

**GENERATOR INTERCONNECTION
SYSTEM IMPACT RESTUDY REPORT**

for integration of the proposed

149 MW [REDACTED] PROJECT

(GI PROJECT #636)

to the

IDAHO POWER COMPANY ELECTRICAL SYSTEM

in

ELMORE COUNTY, ID

for

[REDACTED]

Report v3.0

5/24/2024

OFFICIAL USE ONLY – DO NOT DUPLICATE, DISTRIBUTE, PUBLISH OR SHARE

This report contains Idaho Power Company Critical Energy Infrastructure Information. Distribution of this report must be limited to parties that have entered into a non-disclosure agreement with Idaho Power Company and have a need to know.

Table of Contents

Introduction.....	2
1.0 Study Assumptions.....	2
2.0 Description of Proposed Generating Project.....	3
3.0 Protection and Control.....	4
4.0 Description of Power Flow Cases	4
5.0 Senior-Queued Interconnections	4
6.0 POI Facilities	4
7.0 System Upgrades.....	5
8.0 Voltage	7
9.0 Transient Stability Analysis	7
10.0 Description of Operating Requirements.....	7
11.0 Conclusion	8
APPENDIX A	9
A-1.0 Method of Study	9
A-2.0 Acceptability Criteria.....	9
A-3.0 Grounding Guidance.....	10
A-4.0 Electrical System Protection Guidance	10
A-5.0 WECC Coordinated Off-Nominal Frequency Load Shedding and Restoration Requirements.....	10
Revision History	11

Introduction

Idaho Power Company (Transmission Provider) identified a necessary change to the transmission system models, specifically related to the area around Idaho Power's recently triggered Gateway West (GWW) segment 8 project. As a result, Transmission Provider identified all generation interconnection projects in the area, including [REDACTED] (Interconnection Customer), would require a Generator Interconnection System Impact Restudy (RSIS) be performed.

This report provides the results of the required RSIS performed for the integration of the proposed 149 MW [REDACTED] (the Project) at a single Point of Interconnection (POI) on Idaho Powers Hubbard - Danskin 230 kV line. The Project is located in Elmore County, ID at approximately [REDACTED]. The Project is assigned Generation Interconnection (GI) queue number 636 (GI #636). The Project has an executed Generator Interconnection Agreement (GIA) for Network Resource Interconnection Service (NRIS).

This report documents the basis for and the results of this RSIS for the GI #636 Interconnection Customer. The report describes the study assumptions, the proposed Project, the determination of the Project interconnection requirements, and estimated costs for integration of the Project to the Transmission Provider's transmission system. This report satisfies the SIS requirements of the Idaho Power Tariff.

1.0 Study Assumptions

- For NRIS, additional studies to reduce or eliminate congestion may be required and these studies may identify the need for additional upgrades. NRIS in and of itself does not convey Transmission Service.
- Senior-queued generator interconnection requests that were considered in this study are listed in Section 5.0. If any of these requests are withdrawn, the Transmission Provider reserves the right to restudy this request, and the results and conclusions could significantly change.
- The need for transmission modifications, if any, that may be required to provide NRIS will be evaluated on the basis of 100 percent deliverability of the interconnection request under study.
- Power flow analysis requires WECC base cases to reliably balance under peak load conditions the aggregate of generation in the local area, with the Generating Facility at full output, to the aggregate of the load in the Transmission Provider's Transmission System. However, Idaho Power's balancing authority area has proposed generation in the interconnection queue that far surpasses projected load. To reliably balance the power flow case, it is necessary to assume some portions of other resources are displaced by this Project's output in order to assess the impact of interconnecting this Project's generation and that some generation is being transferred regionally through the transmission system.
- The Most Severe Single Contingency (MSSC) is the balancing contingency event, due to a single contingency, that results in the greatest loss (measured in MW) of resource

output used by the Balancing Authority at the time of the event to meet firm system load and export obligation. Idaho Power’s MSSC is [REDACTED]. An NRIS interconnection request greater than [REDACTED] must mitigate single contingencies that would result in the loss of more than [REDACTED].

- Idaho Power will not mitigate thermal violations with remedial action schemes (RAS) in the GI process.
- The following Transmission Provider planned system improvements were assumed in service:
 - Boardman to Hemingway 500 kV transmission line (Q2 2027)
 - 50% series capacitance compensation on the Kinport to Midpoint 345 kV transmission line (2025)
 - Midpoint Substation T502 500:345 kV transformer (2025)
 - Hemingway to Bowmont 230 kV transmission line (2025)
 - Bowmont to Hubbard 230 kV transmission line (2025)
 - Gateway West Segment 8 (2028)
 - Mayfield 500/230kV Substation (2028)

2.0 Description of Proposed Generating Project

The primary POI for the Project is on the Hubbard - Danskin 230kV line with a maximum injection of 149 MW. The Project’s Commercial Operation Date (COD) is [REDACTED].

Project Location	[REDACTED]
Generator Nameplate Rating	[REDACTED]
Total Output Power Rating	[REDACTED]
Number and Type of Inverters	[REDACTED]
Main Power Transformer	[REDACTED]
Rated Power Factor	[REDACTED]

Table 1. GI #636 Project Specifications

3.0 Protection and Control

Studies indicate that there is adequate load and short circuit interrupting capability on the Transmission Provider's existing 230 kV breakers after this Project is interconnected.

For 230 kV line protection, the Transmission Provider's System Protection Department utilizes permissive and line differential protection schemes integrated with digital communication infrastructure. Idaho Power will require OPGW in the static wire position for any lead-line interconnection facility. Communication infrastructure between the Interconnection Customer's 230 kV collector substation and Idaho Power will be the responsibility of the Interconnection Customer.

The proposed 230 kV [REDACTED] transformer specified in the Project should provide an adequate ground return path for transmission line protection/relaying.

Grounding requirements and acceptability criteria are found in Appendix A.

4.0 Description of Power Flow Cases

For the NRIS study, two power flow cases were used to study the Transmission Provider's transmission system with heavy east-to-west power flow and heavy west-to-east power flow conditions to determine the required Network Transmission Upgrades.

The WECC 2024 Heavy Summer base case was modified to represent a summer month with high west-to-east (eastbound) transfers across Midpoint West.

The WECC 2024 Light Winter base case was modified to represent a shoulder month condition with high east-to-west (westbound) transfers across Idaho-Northwest.

5.0 Senior-Queued Interconnections

Idaho Power generation interconnection projects GI #530, GI #551, GI #556, GI #558, GI #562, GI #567, GI #588, GI #590, GI #624/625, GI #632, GI #633, and GI #635 are senior-queued projects in the affected area of Idaho Power's transmission system. Idaho Power studied GI #636 with all Network Upgrades for the identified senior-queued projects as in-service.

Changes to senior-queued projects, including in-service date and withdrawal from the queue, may trigger a restudy associated with GI #636.

6.0 POI Facilities

Listed below are the required transmission facilities to interconnect the Project at the POI.

The actual station layout and detailed equipment requirements will be determined in the Facilities Restudy should the Interconnection Customer choose to move to that study phase of the interconnection process. In Table 2 below, a summary is provided of the facilities and conceptual costs required to interconnect the GI #636 Project to the Transmission Provider's transmission system.

Item of Work	Estimate
A generation interconnection and protection package at the POI with 3 new 230 kV power circuit breaker and line terminal at the Substation, associated switches, protective relays, 3-phase potential transformers (PTs) and 3-phase current transformers (CTs), SCADA and remote connectivity	\$6,369,600
Subtotal	\$6,369,600
Contingency 20% ⁽¹⁾	\$1,273,920
Total unloaded costs	\$7,643,520
Overheads ⁽²⁾	\$267,523
Total Conceptual-level Cost Estimate ⁽³⁾	\$7,911,043
<p>(1) Contingency is added to cover the unforeseen costs in the estimate. These costs can include unidentified design components, material cost increases, labor estimate shortfalls, etc.</p> <p>(2) Overhead costs cover the indirect costs associated with the Project and are subject to change.</p> <p>(3) This cost estimate includes direct equipment, material, labor, and overheads as shown.</p>	

Table 2. Estimated GI #636 Project’s POI Costs

Note the following regarding Table 2:

- These estimates do not include the cost of the customer’s equipment/facilities or required communication circuits for SCADA, PMU, Protection, and metering.
- These costs assume the use of Idaho Power resources.
- These are non-binding conceptual level cost estimates that will be further refined upon the request and completion of the Facilities Restudy; final charges to the customer will be based on the actual construction costs incurred.
- These costs include both Interconnection Facilities (direct assigned) and Network Resources (reimbursable). These costs will be explicitly broken out in the Facilities Restudy.

The schedule for designing, procuring, and constructing facilities will be developed and optimized during the Facilities Restudy should the Interconnection Customer choose to move to that study phase of the interconnection process.

7.0 System Upgrades

Studies discovered the following overloads in the WECC 2024 Light Winter base case with high east-to-west flows on the Idaho–Northwest path.

Designation	Contingency	Violation
NRIS	Outage of █████ 230kV Line	Thermal Overload of █████ 230kV Line
NRIS	Outage of █████ 230kV Line	Thermal Overload of █████ 230kV Line

Table 3. Contingency Violations

The following are Network Upgrades assigned to GI #636 to mitigate the violations outlined in Table 3.

Item of Work	Estimate
Reconductor █████ 230kV Line with 2 x 795 Tern	\$8,800,000
Reconductor █████ 230kV Line with 2 x 795 Tern	\$12,000,000
Subtotal	\$20,800,000
Contingency 20% ⁽¹⁾	\$4,160,000
Total unloaded costs	\$24,960,000
Overheads ⁽²⁾	\$873,600
Total Conceptual-level Cost Estimate in 2024 dollars ⁽³⁾	\$25,833,600
<p>(1) Contingency is added to cover the unforeseen costs in the estimate. These costs can include unidentified design components, material cost increases, labor estimate shortfalls, etc.</p> <p>(2) Overhead costs cover the indirect costs associated with the Project and are subject to change.</p> <p>(3) This cost estimate includes direct equipment, material, labor, and overheads as shown.</p>	

Table 4. Estimated GI #636 Network Upgrade Costs

In addition to the Network Upgrades identified above, the following contingent facilities associated with senior-queued GI projects #530, #567, #588, and #604 are also required. The construction of these contingent facility upgrades has been advanced for senior-queued project #567. Due to this advancement, the contingent facility upgrades are expected to be completed in March 2025 and are not available to be further advanced at this time.

Designation	Contingent Facility	Estimated In-Service
NRIS	Boise Bench–Hubbard 230kV loop into CHIP	March 2025
NRIS	Rattlesnake–DRAM 230kV loop into CHIP	March 2025

Table 5. GI #636 Contingent Facilities

Along with the contingent facilities associated with senior-queued projects, the Project is contingent on the following Idaho Power planned system improvement that is required to be completed prior to the Project's interconnection.

Designation	Contingent Facility	Estimated In-Service
NRIS	Pleasant Valley Solar to Mayfield 230kV Line	TBD
NRIS	Mayfield 230kV Buildout	TBD

Table 6. GI #636 Contingent Idaho Power Planned Project

8.0 Voltage

A Voltage Stability study was performed using the WECC 2024 Heavy Summer case with Midpoint West west-to-east flows at 105% of the path rating and the WECC 2024 Light Winter case with Idaho–Northwest east-to-west flows at 105% of the path rating. All contingencies solved successfully; there were no voltage stability issues found for the Project.

The Project will be required to control voltage in accordance with a voltage schedule as provided by Idaho Power Load Serving Operations. The Project will be required to manage the real power output of their generation project at the POI. Also, it may be beneficial for the Interconnection Customer, for their own modeling compliance requirements, to install additional PMU devices at their facilities to monitor the generation source.

9.0 Transient Stability Analysis

The WECC 2024 Light Winter operating case and PowerWorld Simulator version 23 analysis tool were used to perform the transient stability analysis.

The results showed no transient stability violations. Per NERC Reliability Standards, the Generator Owner is responsible to ensure the modeling data utilized accurately reflects inverter operations, and to provide updates to Idaho Power if testing or real-time observations indicate a need.

10.0 Description of Operating Requirements

GI #636 will be required to control voltage in accordance with a voltage schedule as provided by Idaho Power Load Serving Operations. The Project will be required to manage the real power output of their generation project at the POI. The Project will be required to operate at 0.95 leading/lagging measured at the high side of the main power transformer to maintain voltage within limits at the POI over the range of real power output.

The Project is required to comply with the applicable Voltage and Current Distortion Limits found in IEEE Standard 519-2014 *IEEE Recommended Practices and Requirements for Harmonic Control in Electrical Power Systems*.

Installation of phasor measurement unit devices at the POI and maintenance costs associated with communication circuits needed to stream PMU data will also be required to be provided to interconnect the Project. The specific costs associated with the Idaho Power requirements for Interconnection Customers with aggregate facilities larger than 20 MW to provide PMU data to Idaho Power will be identified in the Facilities Restudy should the Interconnection Customer choose to proceed to that phase of the interconnection process. Also, it may be beneficial for the Interconnection Customer, for their own modeling compliance requirements, to install additional PMU devices at their facilities to monitor the generations sources separately.

11.0 Conclusion

Interconnection requirements detailed in Section 6.0 totaling \$7,911,043 are required to interconnect the Project at the POI. Additional upgrades and contingent facilities required prior to the Project's interconnection are identified in Section 7.0 totaling \$25,833,260.

APPENDIX A

A-1.0 Method of Study

The power flow case for the System Impact Restudy is built using Western Electricity Coordinating Council (WECC) power flow cases as a base case in Power World Simulator. The base cases are then modified to include the senior-queued generation interconnection projects in Section 5.0 and their respective Network Upgrades and POI facilities. The generation project being studied is then added to the cases with the model provided by the Interconnection Customer at the requested 149 MW at the requested POI. The base cases are then rebalanced such that the applicable WECC transmission paths are at their WECC path rating with reasonable pre-contingency energy transfers utilizing the Idaho Power transmission system. The power flow model is then analyzed using P1 and P2 category contingencies contained in Table 1 of NERC standard TPL-001. WECC and Idaho Power reliability criteria are applied to the results of the contingency analysis and any violations listed in Table 3, are mitigated with Network Upgrades or contingent facilities (see also Section 7.0).

A-2.0 Acceptability Criteria

The following acceptability criteria were used in the power flow analysis to determine under which system configuration modifications may be required:

The continuous rating of equipment is assumed to be the normal thermal rating of the equipment. This rating will be as determined by the manufacturer of the equipment or as determined by Idaho Power. Less than or equal to 100% of continuous rating is acceptable.

Idaho Power's Voltage Operating Guidelines were used to determine voltage requirements on the system. These state, in part, that distribution voltages under normal operating conditions are to be maintained within plus or minus 5% (0.05 per unit) of nominal everywhere on the feeder. Therefore, voltages greater than or equal to 0.95 pu voltage and less than or equal to 1.05 pu voltage are acceptable.

Voltage flicker during starting or stopping the generator is limited to 5% as measured at the point of interconnection, per Idaho Power's T&D Advisory Information Manual.

Idaho Power's Reliability Criteria for System Planning was used to determine proper transmission system operation.

All customer generation must meet IEEE 519 and ANSI C84.1 Standards.

All other applicable national and Idaho Power standards and prudent utility practices were used to determine the acceptability of the configurations considered.

The stable operation of the system requires an adequate supply of volt-amperes reactive (VAr or VARs) to maintain a stable voltage profile under both steady-state and dynamic system conditions. An inadequate supply of VARs will result in voltage decay or even collapse under the worst conditions.

Equipment/line/path ratings used will be those that are in use at the time of the study or that are represented by IPC upgrade projects that are either currently under construction or whose budgets have been approved for construction in the near future. All other potential future ratings

are outside the scope of this study. Future transmission changes may, however, affect current facility ratings used in the study.

A-3.0 Grounding Guidance

IPC requires interconnected transformers on the distribution system to limit their ground fault current to 20 amps at the Point of Interconnection.

A-4.0 Electrical System Protection Guidance

IPC requires electrical system protection per Facility Connection Requirements found on the Idaho Power website,

<https://docs.idahopower.com/pdfs/BusinessToBusiness/FacConnReq.pdf>

A-5.0 WECC Coordinated Off-Nominal Frequency Load Shedding and Restoration Requirements

IPC requires frequency operational limits to adhere to WECC Under-frequency and Over-frequency Limits per the WECC Coordinated Off-Nominal Frequency Load Shedding and Restoration Requirements available upon request.

Revision History

Date	Revision	Initials	Summary of Changes
11/08/2022	1.0	AVD	Initial Report
04/07/2023	2.0	AVD	Optional Study Report
05/24/2024	3.0	JGD	SIS Restudy
5/30/2024	4.0	JGD	Corrected POI location