

**GENERATOR INTERCONNECTION  
SYSTEM IMPACT STUDY REPORT**

for integration of the proposed

**130 MW XXXX XXXX PROJECT**

**(GI PROJECT #654)**

to the

**IDAHO POWER COMPANY ELECTRICAL SYSTEM**

in

**BINGHAM COUNTY, ID**

for

**XXXX XXXX**

**Report v1.0**

**March 11, 2024**

---

**OFFICIAL USE ONLY – DO NOT DUPLICATE, DISTRIBUTE, PUBLISH OR SHARE**

This report contains Idaho Power Company Critical Energy Infrastructure Information. Distribution of this report must be limited to parties that have entered into a non-disclosure agreement with Idaho Power Company and have a need to know.

## Table of Contents

<b>Introduction.....</b>	<b>2</b>
<b>1.0 Study Assumptions.....</b>	<b>2</b>
<b>2.0 Description of Proposed Generating Project.....</b>	<b>3</b>
<b>3.0 Protection and Control.....</b>	<b>3</b>
<b>4.0 Description of Power Flow Cases .....</b>	<b>4</b>
<b>5.0 Senior-Queued Interconnections .....</b>	<b>4</b>
<b>6.0 POI Facilities .....</b>	<b>4</b>
<b>7.0 System Upgrades.....</b>	<b>5</b>
<b>8.0 Voltage .....</b>	<b>6</b>
<b>9.0 Transient Stability Analysis .....</b>	<b>6</b>
<b>10.0 Description of Operating Requirements.....</b>	<b>6</b>
<b>11.0 Conclusion .....</b>	<b>7</b>
<b>APPENDIX A .....</b>	<b>8</b>
<b>A-1.0 Method of Study .....</b>	<b>8</b>
<b>A-2.0 Acceptability Criteria.....</b>	<b>8</b>
<b>A-3.0 Grounding Guidance.....</b>	<b>9</b>
<b>A-4.0 Electrical System Protection Guidance .....</b>	<b>9</b>
<b>A-5.0 WECC Coordinated Off-Nominal Frequency Load Shedding and     Restoration Requirements.....</b>	<b>9</b>
<b>A-6.0 Storing Energy .....</b>	<b>9</b>
<b>Revision History .....</b>	<b>10</b>

## Introduction

XXXX XXXX contracted with Idaho Power Company (Transmission Provider) to perform a Generator Interconnection System Impact Study (SIS) for the integration of the proposed 130 MW XXXX XXXX (the Project) at a single Point of Interconnection (POI) at 138 kV at Idaho Power's 138 kV Pingree Substation. The Project is located in Bingham County, ID at approximately XXXX XXXX. The project is assigned Generation Interconnect (GI) queue number 654 (GI #654).

Following the completion of the Generator Interconnection Agreement (GIA), senior-queued project GI #580 in the electrically relevant area withdrew from Idaho Power's GI queue. This prompted a re-study of GI #654's SIS that is to be studied for Network Resource Interconnection Service (NRIS) per the executed GIA.

This report documents the basis for and the results of the SIS restudy for the GI #654 Interconnection Customer. The report describes the study assumptions, the proposed Project, the determination of the Project interconnection requirements, and estimated costs for integration of the Project to the Transmission Provider transmission system. This report satisfies the SIS requirements of the Idaho Power Tariff.

### 1.0 Study Assumptions

- For NRIS, additional studies to reduce or eliminate congestion may be required and these studies may identify the need for additional upgrades. NR Interconnection Service in and of itself does not convey Transmission Service.
- Senior-queued generator interconnection requests that were considered in this study are listed in Section 5.0. If any of these requests are withdrawn, the Transmission Provider reserves the right to restudy this request, and the results and conclusions could significantly change.
- The need for transmission modifications, if any, that may be required to provide NRIS will be evaluated on the basis of 100 percent deliverability of the interconnection request under study.
- Power flow analysis requires WECC base cases to reliably balance under peak load conditions the aggregate of generation in the local area, with the Generating Facility at full output, to the aggregate of the load in the Transmission Provider's Transmission System. However, Idaho Power's balancing authority area has proposed generation in the interconnection queue that far surpasses projected load. To reliably balance the power flow case, it is necessary to assume some portions of other resources are displaced by this Project's output in order to assess the impact of interconnecting this Project's generation and that some generation is being transferred regionally through the transmission system.
- The Most Severe Single Contingency (MSSC) is the balancing contingency event, due to a single contingency, that results in the greatest loss (measured in MW) of resource output used by the Balancing Authority at the time of the event to meet firm system load and export obligation. Idaho Power's MSSC is 330 MW. An NRIS interconnection

request greater than 330 MW must mitigate single contingencies that would result in the loss of more than 330 MW. This includes, but is not limited to, single contingencies in XXXX XXXX Interconnection Facilities.

- Idaho Power will not mitigate thermal violations with remedial action schemes (RAS) in the generation interconnection process.
- The following Transmission Provider planned system improvements were assumed in service:
  - Boardman to Hemingway 500 kV transmission line (Q2 2026)
  - 50% series capacitance compensation on the Kinport to Midpoint 345 kV transmission line (2025)
  - Midpoint Substation T502 500:345 kV transformer (2025)
  - Hemingway to Bowmont 230 kV transmission line (2025)
  - Bowmont to Hubbard 230 kV transmission line (2025)

## 2.0 Description of Proposed Generating Project

The primary POI for the Project is the 138 kV Pingree Substation with a maximum injection of 130 MW. The Project's Commercial Operation Date (COD) is XXXX.

XXXX XXXX

**Table 1.** GI #654 Project Specifications

## 3.0 Protection and Control

Studies indicate that there is adequate load and short circuit interrupting capability on the Transmission Provider's existing 138 kV breakers after this Project is interconnected.

For 138 kV line protection, the Transmission Provider's System Protection Department utilizes permissive and line differential protection schemes integrated with digital communication infrastructure. Idaho Power will require OPGW in the static wire position for any lead-line interconnection facility or fiber communication between co-located facilities. Communication infrastructure between the interconnection's customer's 138 kV collector substation and Idaho Power will be the responsibility of the interconnection customer.

The proposed 138 kV Wye-Grounded/Wye-Grounded with a Delta tertiary transformer specified in the Project should provide an adequate ground return path for transmission line protection/relaying.

Grounding requirements and acceptability criteria are found in Appendix A.

#### 4.0 Description of Power Flow Cases

For the NRIS study, two power flow cases were used to study the Transmission Provider's transmission system with heavy east to west power flow and a heavy west to east power flow conditions to determine the required Network Transmission Upgrades.

The WECC 2025 Heavy Summer base case was modified to represent a summer month with high west to east (eastbound) transfers across Borah West.

The WECC 2022 Light Winter base case was modified to represent a shoulder month condition with high east to west (westbound) transfers across Borah West.

#### 5.0 Senior-Queued Interconnections

Idaho Power generation interconnection projects GI #558, GI #573, GI #623, GI #633, and GI #641 are senior-queued projects in the affected area of Idaho Power's transmission system. Idaho Power studied GI #654 with all Network Upgrades for the identified senior-queued projects as in-service.

Changes to senior-queued projects, including in-service date and withdrawal from the queue, may trigger a restudy associated with GI #654.

#### 6.0 POI Facilities

Listed below are the required transmission facilities to interconnect the Project at the POI.

The actual station layout and detailed equipment requirements will be determined in the Facilities Study should the interconnection customer choose to move to that study phase of the interconnection process. In Table 2 below, a summary is provided of the facilities and conceptual costs required to interconnect the GI #654 Project to the Transmission Provider's transmission system. These are the same facilities identified in GI #654 Standard Large Generator Interconnection Agreement effective November 2, 2023.

Item of Work	Estimate
IPC interconnection facilities: one 138kV line bay, one steel dead-end structure, one 138kV circuit breaker, two 138kV air-break switches, three CTs, three PTs, one ION 8650A meter, required foundations, bus, bus supports, relay protection equipment and fiber communication equipment	\$413,169

Item of Work	Estimate
Pingree Substation: new line terminal to the 138kV bus. Move existing line to the new line bay. XXXX line will be terminated on the existing bay. One steel dead-end structure, three CCVTs, one wave trap, a control building expansion, associated supports, foundations, relaying, communications, and control equipment.	\$1,203,156
Re-terminate existing 138kV into new line bay.	\$549,494
<b>Subtotal</b>	<b>\$2,165,819</b>
Contingency 20% <sup>(1)</sup>	\$433,163
<b>Total unloaded costs</b>	<b>\$2,598,982</b>
Overheads <sup>(2)</sup>	\$181,928
<b>Total Conceptual-level Cost Estimate <sup>(3)</sup></b>	<b>\$2,780,911</b>
<p>(1) Contingency is added to cover the unforeseen costs in the estimate. These costs can include unidentified design components, material cost increases, labor estimate shortfalls, etc.</p> <p>(2) Overhead costs cover the indirect costs associated with the Project and are subject to change.</p> <p>(3) This cost estimate includes direct equipment, material, labor, and overheads as shown.</p>	

**Table 2.** Estimated GI #654 Project's POI Costs

Note the following regarding Table 2:

- These estimates do not include the cost of the customer's equipment/facilities or required communication circuits for SCADA, Phasor Measurement Unit (PMU), Protection, and metering.
- These costs assume the use of Idaho Power resources.
- These are non-binding conceptual level cost estimates that will be further refined upon the request and completion of the Facilities Study; final charges to the customer will be based on the actual construction costs incurred.
- These costs include both Interconnection Facilities (direct assigned) and Network Resources (reimbursable). These costs will be explicitly broken out in the Facilities Study.

The schedule for designing, procuring, and constructing facilities will be developed and optimized during the Facilities Study should the generation interconnection customer choose to move to that study phase of the interconnection process.

## 7.0 System Upgrades

Studies discovered the following overloads in the WECC 2025 Heavy Summer base case with high West to East flows on the Borah West path.

Designation	Contingency	Violation
NRIS	XXXX XXXX	Thermal Overload of 161:138 kV transformer
NRIS	XXXX XXXX	Thermal Overload of 161:138 kV transformer

**Table 3.** Contingency Violations

The following are Contingent Facilities assigned to GI #654 to mitigate the violations outlined in Table 3. See appendix A-6.0 for network upgrades and contingent facilities required for charging energy storage devices from Idaho Power’s Transmission System.

Designation	Contingent Facility	Estimate	Estimated In-Service
NRIS	Replace XXXX XXXX 135 MVA 161:138 kV transformer	\$4,862,444	December 2024

**Table 4.** Contingency facilities assigned to GI #654

## 8.0 Voltage

A Voltage Stability study was performed using the WECC 2025 Heavy Summer case with Borah West West-to-East flows at 105% of the path rating and the WECC 2022 Light Winter case with Borah West East-to-West flows at 105% of the path rating. All contingencies solved successfully, there were no voltage stability issues found for the Project.

The Project will be required to control voltage in accordance with a voltage schedule as provided by Idaho Power Load Serving Operations. The Project will be required to manage the real power output of their generation project at the POI. Also, it may be beneficial for XXXX XXXX, for their own modeling compliance requirements, to install additional PMU devices at their facilities to monitor the generation source.

## 9.0 Transient Stability Analysis

The WECC 2025 Heavy Summer case and PowerWorld Simulator version 23 analysis tool were used to perform the transient stability analysis.

The results showed no transient stability violations. It is the responsibility (per NERC Standards) of the Generator Owner to ensure the modeling data utilized accurately reflects inverter operations, and to provide updates to Idaho Power if testing or real-time observations indicate a need.

## 10.0 Description of Operating Requirements

GI #654 will be required to control voltage in accordance with a voltage schedule as provided by Idaho Power Load Serving Operations. The Project will be required to manage the real power output of their generation project at the POI. The Project will be required to operate at 0.95

leading/lagging measured at the high side of the main power transformer to maintain voltage within limits at the POI over the range of real power output.

The Project is required to comply with the applicable Voltage and Current Distortion Limits found in IEEE Standard 519-2014 *IEEE Recommended Practices and Requirements for Harmonic Control in Electrical Power Systems*.

Installation of phasor measurement unit devices at the POI and maintenance costs associated with communication circuits needed to stream PMU data will also be required to be provided to interconnect the Project. The specific costs associated with the IPC requirements for interconnection customers with aggregate facilities larger than 20 MW to provide PMU data to IPC will be identified in the Facilities Study should the generation interconnection customer choose to proceed to that phase of the interconnection process. Also, it may be beneficial for XXXX XXXX, for their own modeling compliance requirements, to install additional PMU devices at their facilities to monitor the generations sources separately.

## **11.0 Conclusion**

Interconnection requirements detailed in Section 6.0 totaling \$2,780,911 are required to interconnect the Project at the POI. Additional Contingent Facilities are required for NRIS totaling \$4,862,444 are identified in Section 7.0. The Network Upgrade assigned to GI #654 totaling \$10,409,112 and Contingent Facilities totaling \$39,138,283 listed in Appendix A-6.0 are required to mitigate overloads during battery system charging and will be required to charge from the Idaho Power Transmission System.



## APPENDIX A

### A-1.0 Method of Study

The power flow case for the System Impact study is built using Western Electricity Coordinating Council (WECC) power flow cases as a base case in Power World Simulator. The base cases are then modified to include the senior-queued generation interconnection projects in Section 5.0 and their respective network upgrades and POI facilities. The generation project being studied is then added to the cases with the model provided by XXXX XXXX at the requested 130 MW at the requested POI. The base cases are then rebalanced such that the applicable WECC transmission paths are at their WECC path rating with reasonable pre-contingency energy transfers utilizing the Idaho Power transmission system. The power flow model is then analyzed using P1 and P2 category contingencies contained in Table 1 of NERC standard TPL-001. WECC and Idaho Power reliability criteria are applied to the results of the contingency analysis and any violations listed in Table 3, are mitigated with Network Upgrades or contingent facilities, (see also Section 7.0).

### A-2.0 Acceptability Criteria

The following acceptability criteria were used in the power flow analysis to determine under which system configuration modifications may be required:

The continuous rating of equipment is assumed to be the normal thermal rating of the equipment. This rating will be as determined by the manufacturer of the equipment or as determined by Idaho Power. Less than or equal to 100% of continuous rating is acceptable.

Idaho Power's Voltage Operating Guidelines were used to determine voltage requirements on the system. These state, in part, that distribution voltages under normal operating conditions are to be maintained within plus or minus 5% (0.05 per unit) of nominal everywhere on the feeder. Therefore, voltages greater than or equal to 0.95 pu voltage and less than or equal to 1.05 pu voltage are acceptable.

Voltage flicker during starting or stopping the generator is limited to 5% as measured at the point of interconnection, per Idaho Power's T&D Advisory Information Manual.

Idaho Power's Reliability Criteria for System Planning was used to determine proper transmission system operation.

All customer generation must meet IEEE 519 and ANSI C84.1 Standards.

All other applicable national and Idaho Power standards and prudent utility practices were used to determine the acceptability of the configurations considered.

The stable operation of the system requires an adequate supply of volt-amperes reactive (VAR or VARs) to maintain a stable voltage profile under both steady-state and dynamic system conditions. An inadequate supply of VARs will result in voltage decay or even collapse under the worst conditions.

Equipment/line/path ratings used will be those that are in use at the time of the study or that are represented by IPC upgrade projects that are either currently under construction or whose budgets have been approved for construction in the near future. All other potential future ratings

are outside the scope of this study. Future transmission changes may, however, affect current facility ratings used in the study.

### A-3.0 Grounding Guidance

IPC requires interconnected transformers on the distribution system to limit their ground fault current to 20 amps at the Point of Interconnection.

### A-4.0 Electrical System Protection Guidance

IPC requires electrical system protection per Facility Connection Requirements found on the Idaho Power website,

<https://docs.idahopower.com/pdfs/BusinessToBusiness/FacConnReq.pdf>

### A-5.0 WECC Coordinated Off-Nominal Frequency Load Shedding and Restoration Requirements

IPC requires frequency operational limits to adhere to WECC Under-frequency and Over-frequency Limits per the WECC Coordinated Off-Nominal Frequency Load Shedding and Restoration Requirements available upon request.

### A-6.0 Storing Energy

The energy storage system (ESS) component of the Project was studied charging from the grid in steady state under N-0 (no contingencies) conditions which resulted in an overload of the XXXX XXXX and XXXX XXXX 138 kV transmission lines. The network upgrades listed below are required to mitigate the overload during charging and will be required to charge from the Idaho Power Transmission System. However, there may be times during the year where system load in the local area will prevent charging of the ESS at full capacity; for example, a forced outage that would require Idaho Power to curtail charging. The POI is on the radial XXXX 138 kV line, during summer months the load at XXXX XXXX ranges from XX MW and remains higher than XX MW for weeks at a time. Should the Project require non-curtailable charging of the energy storage device then Point-to-Point firm transmission service from the energy market to the battery and from the Project to the point of delivery would be needed.

Assigned	Network Upgrade	Estimate	Estimated In-Service
Idaho Power	XXXX XXXX 138 kV	\$27,996,235	March 2027
Idaho Power	XXXX XXXX 138 kV	\$11,142,048	June 2026
GI #654	Extend 138 kV from XXXX XXXX 138 kV	\$10,409,112	GIA Milestone

**Table 5.** GI #654 Required battery charging Network Upgrades.

**Revision History**

<b>Date</b>	<b>Revision</b>	<b>Initials</b>	<b>Summary of Changes</b>
02/06/2023	1.0	PTP	Initial System Impact Study Report
03/11/2024	2.0	PTP	System Impact Restudy, GI 580 withdrawal