

**GENERATOR INTERCONNECTION
SYSTEM IMPACT STUDY REPORT**

for integration of the proposed

**200 MW XXXX XXXX XXXX PROJECT
(GI PROJECT #641)**

to the

IDAHO POWER COMPANY ELECTRICAL SYSTEM

in

POWER COUNTY, ID

for

XXXX XXXX XXXX

Report v.1

September 19th, 2022

OFFICIAL USE ONLY

DO NOT DUPLICATE, DISTRIBUTE, PUBLISH OR SHARE

*This report contains Idaho Power Company Critical Energy Infrastructure Information (CEII).
Distribution of this report must be limited to parties that have entered into a non-disclosure
agreement with Idaho Power Company and have a need to know.*

Table of Contents

1.0	Introduction.....	3
2.0	Summary.....	4
3.0	Scope of Interconnection System Impact Study.....	5
4.0	Contingent Facilities	5
5.0	Description of Proposed Generating Project.....	6
6.0	Energy Resource Interconnection Service (ERIS).....	6
6.1	Description of Substation/Transmission Facilities	6
6.2	Description of Distribution Facilities.....	7
6.3	Short Circuit Study Results.....	7
6.4	Electric System Protection Results and Grounding Requirements	7
6.5	Energy Resource Interconnection Service Cost Estimate	7
7.0	Network Resource Interconnection Service (NRIS)	8
7.1	Description of Power Flow Cases.....	8
7.2	Network Resource Interconnection Service Transmission Upgrades	8
7.3	Network Resource Interconnection Service Cost Estimate.....	8
8.0	Voltage Stability Analysis	9
9.0	Transient Stability Analysis.....	9
10.0	Description of Operating Requirements.....	9
11.0	Conclusion	10
APPENDIX A		11
A-1.0	Method of Study	11
A-2.0	Acceptability Criteria.....	11
A-3.0	Grounding Guidance.....	12
A-4.0	Electrical System Protection Guidance	12
A-5.0	WECC Coordinated Off-Nominal Frequency Load Shedding and Restoration Requirements.....	12
Revision History		12

OFFICIAL USE ONLY

DO NOT DUPLICATE, DISTRIBUTE, PUBLISH OR SHARE

*This report contains Idaho Power Company Critical Energy Infrastructure Information (CEII).
Distribution of this report must be limited to parties that have entered into a non-disclosure
agreement with Idaho Power Company and have a need to know.*

1.0 Introduction

XXXX XXXX XXXX has contracted with Idaho Power Company (“Transmission Provider”) to perform a Generator Interconnection System Impact Study (SIS) for the integration of the proposed 200 MW XXXX XXXX XXXX Project (the Project). The Project location is in Power County, ID at approximately XXXX N, XXXX W. The project is Generation Interconnect (GI) queue number 641 (GI #641). The Project has chosen in the System Impact Study to be studied for Energy Resource Interconnection Service (ERIS) and Network Resource Interconnection Service (NRIS).

Energy Resource Interconnection Service and/or Network Resource Interconnection Service in and of themselves do not convey transmission service. In addition to Network Upgrades identified in the Interconnection System Impact Study:

- For Energy Resource Interconnection Service, the Interconnection Customer's ability to inject its Large Generating Facility output beyond the Point of Interconnection will depend on the existing capacity of Transmission Provider's Transmission System at such time as a transmission service request is made that would accommodate such delivery. The provision of firm Point-to-Point Transmission Service or Network Integration Transmission Service may require the construction of additional Network Upgrades.
- For Network Resource Interconnection Service, additional studies to reduce or eliminate congestion may be required and these studies may identify the need for additional upgrades. To the extent Interconnection Customer enters an arrangement for long term transmission service for deliveries from the Large Generating Facility outside Transmission Provider's Transmission System, such request may require additional studies and upgrades in order for Transmission Provider to grant such request.

The Project has applied to connect to Idaho Power’s transmission system for an injection of 200 MW at a single Point of Interconnection (POI) at 230 kV. The POI is located at Idaho Power’s Brady 230 kV substation (BRDY 230 kV).

This report documents the basis for and the results of this System Impact Study for the GI #641 Generation Interconnection Customer. The report describes the proposed Project, the determination of the Project interconnection requirements, and estimated costs for integration of the Project to the Transmission Provider transmission system. This report satisfies the SIS requirements of the Idaho Power Tariff.

OFFICIAL USE ONLY

DO NOT DUPLICATE, DISTRIBUTE, PUBLISH OR SHARE

This report contains Idaho Power Company Critical Energy Infrastructure Information (CEII). Distribution of this report must be limited to parties that have entered into a non-disclosure agreement with Idaho Power Company and have a need to know.

2.0 Summary

The impact to the Idaho Power transmission system of interconnecting the Project to BRDY 230 kV was evaluated.

The Project will be required to control voltage in accordance with a voltage schedule as provided by Idaho Power Grid Operations. The Project will be required to manage the real power output of their generation project at the POI. Also, it may be beneficial for XXXX XXXX XXXX , for their own modeling compliance requirements, to install additional PMU devices at their facilities to monitor the generation source.

The total Energy Resource Interconnection Service generation interconnection preliminary cost estimate to interconnect the Project at the POI is \$2,484,720. See Section 6.5 Energy Resource Interconnection Service Cost Estimate for the required facilities and cost breakdowns.

No additional upgrades are required for Network Resource Interconnection Service. The total Network Resource Interconnection Service generation interconnection preliminary cost estimate to interconnect the Project at the POI is \$2,484,720. See Section 7.3 Network Resource Interconnection Service Cost Estimate for the required facilities and cost breakdowns.

The Project is a standalone battery energy storage system (BESS) project; it has been assumed that the BESS will be charged by the Idaho Power transmission system. Idaho Power will require an additional study to evaluate charging the BESS via IPC's transmission system.

The cost estimates include 20% contingency and 6.25% overhead. These are cost estimates only and final charges to the customer will be based on the actual construction costs incurred. It should be noted that the preliminary cost estimates do not include the cost of the customer's owned equipment.

The schedule for designing, procuring, and constructing facilities will be developed and optimized during the Facility Study should the generation interconnection customer choose to move to that study phase of the interconnection process.

OFFICIAL USE ONLY

DO NOT DUPLICATE, DISTRIBUTE, PUBLISH OR SHARE

This report contains Idaho Power Company Critical Energy Infrastructure Information (CEII). Distribution of this report must be limited to parties that have entered into a non-disclosure agreement with Idaho Power Company and have a need to know.

3.0 Scope of Interconnection System Impact Study

The Interconnection System Impact Study was done and prepared in accordance with the Transmission Provider's Standard Generator Interconnection Procedures to provide an evaluation of the system impact of the interconnection of the proposed generating project to the Idaho Power system. As listed in the Interconnection System Impact Study Agreement, the Interconnection System Impact Study report provides the following information:

- identification of any circuit breaker short circuit capability limits exceeded as a result of the interconnection;
- identification of any thermal overload or voltage limit violations resulting from the interconnection;
- identification of any instability or inadequately damped response to system disturbances resulting from the interconnection and
- description and non-binding, good faith estimated cost of facilities required to interconnect the Large Generating Facility to the Transmission System and to address the identified short circuit, instability, and power flow issues.

All other proposed Generation projects prior to this Project in the Generator Interconnect queue were considered in this study. A current list of these projects can be found in the Generation Interconnection folder located on the Idaho Power web site at the link shown below:

<http://www.oatioasis.com/ipco/index.html>.

4.0 Contingent Facilities

Idaho Power studied GI #641 with all Network Upgrades identified for senior queued projects as in-service. GI #641 Energy Resource Interconnection Service and Network Resource Interconnection Service is not contingent upon upgrades associated with any senior queued project. Changes to senior queued projects including in-service date and withdrawal from the queue, may trigger a restudy associated with GI #641.

OFFICIAL USE ONLY

DO NOT DUPLICATE, DISTRIBUTE, PUBLISH OR SHARE

This report contains Idaho Power Company Critical Energy Infrastructure Information (CEII). Distribution of this report must be limited to parties that have entered into a non-disclosure agreement with Idaho Power Company and have a need to know.

5.0 Description of Proposed Generating Project

The primary POI for GI #641 is BRDY 230 kV. GI #641 Project's maximum generation is 200 MW injection at the POI. The Project's Commercial Operation Date (COD) is XXXX.

POI Location	42.772908 N, -112.870406 W
Generator Nameplate Rating	259.2 MVA
Total Output Power Rating	200 MW to POI
Number and Type of Inverters	(216) XXXX inverters
Generator Step-Up Transformer	(2) 78/104/130 MVA
Inverter Step-Up Transformer	(72) XXXX
Rated Power Factor	0.812 Leading/Lagging (inverter at max P rating) Model provided .786 leading/lagging at generator
Interconnection Voltage	230 kV

Table 1. GI #641 Project Specifications

6.0 Energy Resource Interconnection Service (ERIS)

ERIS allows the Interconnection Customer to connect its Generating Facility to Transmission Provider's transmission system and to be eligible to deliver electric output using firm or non-firm transmission capacity on an as available basis.

The GI #641 Project has applied to connect to the Idaho Power transmission system for an injection of 200 MW with a new interconnection at BRDY 230 kV. All generation projects in the area ahead of this Project in the IPC generation queue and their associated transmission system improvements were modeled in a power flow analysis to evaluate the system impact of interconnecting GI #641. Power flow analysis indicates that the Project's full output of 200 MW can be interconnected at the POI.

6.1 Description of Substation/Transmission Facilities

As an ERIS, a Transmission Service Request will be required to determine the specific Network Upgrades required to deliver the Project output to a designated point of delivery. Listed below are the required transmission facilities to interconnect the Project for ERIS:

- Construction of a new 230 kV terminal at the Brady substation
- A generation interconnection and protection package at the POI with 230 kV power circuit breaker, associated switches, protective relays, 3-phase potential transformers (PTs) and 3-phase current transformers (CTs), SCADA and remote connectivity
- Expansion of the Brady Substation for the new 230 kV terminal

OFFICIAL USE ONLY

DO NOT DUPLICATE, DISTRIBUTE, PUBLISH OR SHARE

This report contains Idaho Power Company Critical Energy Infrastructure Information (CEII). Distribution of this report must be limited to parties that have entered into a non-disclosure agreement with Idaho Power Company and have a need to know.

The actual station layout and detailed equipment requirements will be determined in the Facility Study should the interconnection customer choose to move to that study phase of the interconnection process.

6.2 Description of Distribution Facilities

No distribution facilities are owned or operated by Idaho Power in the area.

6.3 Short Circuit Study Results

Studies indicate that there is adequate load and short circuit interrupting capability on the Transmission Provider’s existing 230 kV breakers after this Project is interconnected.

6.4 Electric System Protection Results and Grounding Requirements

For 230 kV line protection, the Transmission Provider’s System Protection Department utilizes permissive and line differential protection schemes integrated with digital communication infrastructure. Communication infrastructure for the interconnection customer’s 230 kV Interconnection Facilities will be the responsibility of said interconnection customer.

The proposed 230 kV Wye-Grounded/Delta transformer specified in the Project should provide an adequate ground return path for transmission line protection/relaying. Grounding requirements and acceptability criteria are found in Appendix A.

6.5 Energy Resource Interconnection Service Cost Estimate

In Table 2 below, a summary is provided of the facilities and conceptual costs required to interconnect the GI #641 Project to the Transmission Provider’s transmission system.

Item of Work	Estimate
Generation interconnection and protection package at POI, station expansion	\$1,948,800
Contingency 20% (1)	\$389,760
Total unloaded costs	\$2,338,560
Overheads (2)	\$146,160
Total Conceptual-level Cost Estimate in 2021 dollars (3)	\$2,484,720

Table 2. Estimated GI #641 Project’s Energy Resource Generation Interconnection Costs

(1) Contingency is added to cover the unforeseen costs in the estimate. These costs can include unidentified design components, material cost increases, labor estimate shortfalls, etc.

(2) Overhead costs cover the indirect costs associated with the Project.

OFFICIAL USE ONLY

DO NOT DUPLICATE, DISTRIBUTE, PUBLISH OR SHARE

This report contains Idaho Power Company Critical Energy Infrastructure Information (CEII). Distribution of this report must be limited to parties that have entered into a non-disclosure agreement with Idaho Power Company and have a need to know.

(3) This cost estimate includes direct equipment, material, labor, and overheads as shown.

- Note that these estimates do not include the cost of the customer's equipment/facilities or required communication circuits for SCADA, PMU, and metering.
- Note that the overhead rates are subject to change during the year.
- Note that these costs assume the use of in-house resources.
- These are estimated costs only and final charges to the customer will be based on the actual construction costs incurred.
- These are non-binding conceptual level cost estimates that will be further refined upon the request and completion of the Facility Study.

The schedule for designing, procuring, and constructing facilities will be developed and optimized during the Facility Study should the generation interconnection customer choose to move to that study phase of the interconnection process.

7.0 Network Resource Interconnection Service (NRIS)

NRIS allows the Interconnection Customer to integrate its Generating Facility with the Transmission Provider's Transmission System in a manner comparable to that in which the Transmission Provider integrated its generating facilities to serve native load customers. The transmission system is studied under a variety of conditions to determine the transmission improvements/upgrades which are necessary. NRIS in and of itself does not convey Transmission Service.

7.1 Description of Power Flow Cases

For the NRIS study, two power flow cases were used to study the Transmission Provider's transmission system with heavy load conditions and lightly loaded conditions to determine the required Network Transmission Upgrades.

The WECC 2025 Heavy Summer base case was modified to represent a summer month with high west to east (eastbound) transfers across Borah West.

The WECC 2022 Light Winter base case was modified to represent a shoulder month condition with high east to west (westbound) transfers across Borah West.

7.2 Network Resource Interconnection Service Transmission Upgrades

There were no Network Upgrades or contingent facilities identified for GI# 641.

7.3 Network Resource Interconnection Service Cost Estimate

The Network Resource Interconnection Service and Energy Resource Interconnection Service cost estimates are the same as there are no additional upgrades for NRIS.

OFFICIAL USE ONLY

DO NOT DUPLICATE, DISTRIBUTE, PUBLISH OR SHARE

This report contains Idaho Power Company Critical Energy Infrastructure Information (CEII). Distribution of this report must be limited to parties that have entered into a non-disclosure agreement with Idaho Power Company and have a need to know.

The schedule for designing, procuring, and constructing facilities will be developed and optimized during the Facility Study should the generation interconnection customer choose to move to that study phase of the interconnection process.

8.0 Voltage Stability Analysis

A Voltage Stability study was performed using the WECC 2025 Heavy Summer case with Borah West West-to-East flows at 105% of the path rating and the WECC 2022 Light Winter case with Borah West East-to-West flows at 105% of the path rating. All contingencies solved successfully, there were no voltage stability issues found for the Project.

9.0 Transient Stability Analysis

The WECC 2021 Light Winter operating case and PowerWorld Simulator version 22 analysis tool were used to perform the transient stability analysis.

The results showed no transient stability violations. It is the responsibility (per NERC Standards) of the Generator Owner to ensure the modeling data utilized accurately reflects inverter operations, and to provide updates to Idaho Power if testing or real-time observations indicate a need.

10.0 Description of Operating Requirements

GI #641 will be required to control voltage in accordance with a voltage schedule as provided by Idaho Power Grid Operations. The Project will be required to manage the real power output of their generation project at the POI. The Project will be required to operate at .95 leading/lagging measured at the high side of the main power transformer to maintain voltage within limits at the POI over the range of real power output.

The Project is required to comply with the applicable Voltage and Current Distortion Limits found in IEEE Standard 519-1992 *IEEE Recommended Practices and Requirements for Harmonic Control in Electrical Power Systems*.

Installation of phasor measurement unit devices at the POI and maintenance costs associated with communication circuits needed to stream PMU data will also be required to be provided to interconnect GI #641. The specific costs associated with the IPC requirements for interconnection customers with aggregate facilities larger than 20 MW to provide PMU data to IPC will be identified in the Facility Study should the generation interconnection customer choose to proceed to that phase of the interconnection process. Also, it may be beneficial for XXXX XXXX XXXX , for their own modeling compliance requirements, to install additional PMU devices at their facilities to monitor the generations sources separately.

OFFICIAL USE ONLY

DO NOT DUPLICATE, DISTRIBUTE, PUBLISH OR SHARE

This report contains Idaho Power Company Critical Energy Infrastructure Information (CEII). Distribution of this report must be limited to parties that have entered into a non-disclosure agreement with Idaho Power Company and have a need to know.

11.0 Conclusion

GI #641 can be interconnected to the Idaho Power transmission system.

Interconnection requirements detailed in Section 6.5 totaling \$2,484,720 are required to interconnect the Project for Energy Resource Interconnection Service at the proposed POI at BRDY 230 kV. No additional upgrades were identified for the integration of the Project for Network Resource Interconnection Service totaling \$2,484,720.

The Project is a standalone battery energy storage system (BESS) project; it has been assumed that the BESS will be charged by the Idaho Power transmission system. Idaho Power will require an additional study to evaluate charging the BESS via IPC's transmission system.

Energy Resource Interconnection Service or Network Resource Interconnection Service does not in any way convey any right to deliver electricity to any specific customer or point of delivery. A Transmission Service Request will be required to study the Transmission System Impacts.

OFFICIAL USE ONLY

DO NOT DUPLICATE, DISTRIBUTE, PUBLISH OR SHARE

***This report contains Idaho Power Company Critical Energy Infrastructure Information (CEII).
Distribution of this report must be limited to parties that have entered into a non-disclosure
agreement with Idaho Power Company and have a need to know.***

APPENDIX A

A-1.0 Method of Study

The System Impact Study plan inserts the Project up to the maximum requested injection into the selected Western Electricity Coordinating Council (WECC) power flow case and then, using Power World Simulator or GE's Positive Sequence Load Flow (PSLF) analysis tool, examines the impacts of the new resource on Idaho Power's transmission system (lines, transformers, etc.) within the study area under various operating and outage scenarios. The WECC and Idaho Power reliability criteria and Idaho Power operating procedures were used to determine the acceptability of the configurations considered. The WECC case is a recent case modified to simulate stressed but reasonable pre-contingency energy transfers utilizing the IPC system. For distribution feeder analysis, Idaho Power utilizes DNV·GL's Synergi Electric software and EPRI's OpenDSS software.

A-2.0 Acceptability Criteria

The following acceptability criteria were used in the power flow analysis to determine under which system configuration modifications may be required:

The continuous rating of equipment is assumed to be the normal thermal rating of the equipment. This rating will be as determined by the manufacturer of the equipment or as determined by Idaho Power. Less than or equal to 100% of continuous rating is acceptable.

Idaho Power's Voltage Operating Guidelines were used to determine voltage requirements on the system. These state, in part, that distribution voltages under normal operating conditions are to be maintained within plus or minus 5% (0.05 per unit) of nominal everywhere on the feeder. Therefore, voltages greater than or equal to 0.95 pu voltage and less than or equal to 1.05 pu voltage are acceptable.

Voltage flicker during starting or stopping the generator is limited to 5% as measured at the point of interconnection, per Idaho Power's T&D Advisory Information Manual.

Idaho Power's Reliability Criteria for System Planning was used to determine proper transmission system operation.

All customer generation must meet IEEE 519 and ANSI C84.1 Standards.

All other applicable national and Idaho Power standards and prudent utility practices were used to determine the acceptability of the configurations considered.

The stable operation of the system requires an adequate supply of volt-amperes reactive (VAr or VARs) to maintain a stable voltage profile under both steady-state and dynamic system conditions. An inadequate supply of VARs will result in voltage decay or even collapse under the worst conditions.

Equipment/line/path ratings used will be those that are in use at the time of the study or that

OFFICIAL USE ONLY

DO NOT DUPLICATE, DISTRIBUTE, PUBLISH OR SHARE

This report contains Idaho Power Company Critical Energy Infrastructure Information (CEII). Distribution of this report must be limited to parties that have entered into a non-disclosure agreement with Idaho Power Company and have a need to know.

are represented by IPC upgrade projects that are either currently under construction or whose budgets have been approved for construction in the near future. All other potential future ratings are outside the scope of this study. Future transmission changes may, however, affect current facility ratings used in the study.

A-3.0 Grounding Guidance

IPC requires interconnected transformers on the distribution system to limit their ground fault current to 20 amps at the Point of Interconnection.

A-4.0 Electrical System Protection Guidance

IPC requires electrical system protection per Facility Connection Requirements found on the Idaho Power Web site,

<https://docs.idahopower.com/pdfs/BusinessToBusiness/FacConnReq.pdf>

A-5.0 WECC Coordinated Off-Nominal Frequency Load Shedding and Restoration Requirements

IPC requires frequency operational limits to adhere to WECC Under-frequency and Over-frequency Limits per the WECC Coordinated Off-Nominal Frequency Load Shedding and Restoration Requirements available upon request.

Revision History

Date	Revision	Initials	Summary of Changes
09/19/2022	1	PTP	Initial Report

OFFICIAL USE ONLY

DO NOT DUPLICATE, DISTRIBUTE, PUBLISH OR SHARE

This report contains Idaho Power Company Critical Energy Infrastructure Information (CEII). Distribution of this report must be limited to parties that have entered into a non-disclosure agreement with Idaho Power Company and have a need to know.